



Palermo

- 18 watt 6V6 Class AB power amp (36 watt EL34 optional)
- JJ ECC83s 1st and 2nd gain stage
- JJ ECC83s phase inverter
- Volume control
- 4 position Schizo tone stack gain control
- 3 position Bright switch
- 3 position Standby switch for 18 and 9 watt operation (36 and 18 with EL34's)
- Single 8 ohm speaker out
- Power amp input
- 1x10 combo Celestion G10 or Custom Eminence 8 ohm (not available on EL34 version)
- 1x12 combo Celestion G12H 8 ohm (Celestion V30 8 ohm for EL34 version)

DIMENSIONS and WEIGHTS: Are subject to change anytime, Please measure *your* amp carefully if a Custom Case is being made. *Add 3/4 inch for each, handle and rubber feet.*

18W Head:	7.50" H	18.375" W	7" D	16 pounds
36W Head:	8.25" H	18.375" W	7" D	20 pounds
1x10 combo:	13.625" H	18" W	10" D	37 pounds 18W
1x12 combo:	16.625" H	20.75" W	10.625" D	43 pounds 18W
1x12 combo:	20.75" H	20.75 W	10.625" D	50 pounds 36W